

# Digital Bench Scale

Model: WS201

The WS201 is a general purpose digital bench scale suitable for a wide range of weighing applications. It features high resolution with accurate counting functionality and can be powered by standard batteries which makes it easily portable. Weigh up to 20 kilos in as low as 1 gram increments.

### FEATURES WS201

- general purpose, high resolution bench top scale
- sharp easy to read 20mm high LCD display with back light
- display backlight function
- convenient multiple weighing units, kg / g / lb / oz
- counting function with 10, 20, 50 or 100 piece entry
- net / gross weight display with tare weight entry key
- AC/DC adaptor and/or battery operation to suit your needs
- auto power off function programmable to 5, 10 or 15 minutes
- battery life up to 260 hours continuous use with no back light, up to 160 hours with back light enabled
- removable stainless steel weigh platter for ease of cleaning
- replaceable clear protective cover



#### **VARIATIONS**

Model Number	Max Capacity	Graduation	Platform Size (mm)	Overall Dimensions (mm)
WS2012K	2 kg	0.1 g	210 (W) x 190 (D)	210 (W) x 270 (D) x 100 (H)
WS2014K	4 kg	0.2 g	210 (W) x 190 (D)	210 (W) x 270 (D) x 100 (H)
WS20110K	10 kg	0.5 g	210 (W) x 190 (D)	210 (W) x 270 (D) x 100 (H)
WS20120K	20 kg	1 g	210 (W) x 190 (D)	210 (W) x 270 (D) x 100 (H)

Specifications may change without notice



Freephone: 0800 800 379



## Digital Bench Scale

Model: WS201

### ORDER CODES FOR OPTIONS & SPARE PARTS

Order Code	Description
RD0344	AC Adaptor
OR0792	C Size Battery (requires 4)
RD0345	Clear Protective Cover

### **SPECIFICATIONS**

Legal for Trade Use	No
Scale Type	Bench
Type of Display	Digital Backlit LCD
Number of Displays	1
Weighing Units	kg / g / lb / oz
Checkweighing Function	No
Counting Function	Yes
Price Computing Function	No
Built-in Label Printer	No
Power	Battery Mains Power
Environment Suitability	Dry
Ingress Protection Rating	No
Comm Ports	No



Specifications may change without notice

Freephone: 0800 800 379